

DIMMER COMPATIBILITY
200 SERIES
DRIVER MODELS: DIM1-2 / DIM3-2
LED MODELS: HI-3000 / WD-3018



www.8lighting.com

No.8 Lighting Driver Model	No.8 Lighting LED Model	Dimmer Manufacturer	Dimmer Model/Family	Dimmer Model Tested	Voltage	Dimmer Type	Product Type	Recommended Trim Settings		Dimming Range	
								High-End (%)	Low-End (%)	High-End (%)	Low-End (%)
DIM1-2											
DIM1-2	HI	Lutron	Caseta Wireless C-L	PD-6WCL-WH	120	Forward Phase	Wallbox	Low-End Trim Required		97.6%	0.2%
DIM1-2	WD/WD-2							95.0%	0.4%		
DIM1-2	HI	Lutron	Maestro Wireless C-L	MRF2-6CL-WH	120	Forward Phase	Wallbox	Low-End Trim Required		97.8%	0.4%
DIM1-2	WD/WD-2							99.0%	0.4%		
DIM1-2	HI	Lutron	Maestro Wireless ND	MRF2-6ND-120-WH	120	Forward Phase	Wallbox	-	-	99.6%	0.4%
DIM1-2	WD/WD-2							-	-	99.9%	0.2%
DIM1-2	HI	Lutron	Maestro Wireless ELV	MRF2-6ELV-120-WH	120	Reverse Phase	Wallbox	-	-	90.7%	0.2%
DIM1-2	WD/WD-2							-	-	92.0%	0.2%
DIM1-2	HI	Lutron	RadioRA 2	RRD-10ND-WH	120	Forward Phase	Wallbox/Residential System	-	-	99.7%	0.2%
DIM1-2	WD/WD-2							-	-	99.5%	0.2%
DIM1-2	HI	Lutron	RadioRA 2	RRD-6NA-WH	120	Reverse Phase	Wallbox/Residential System	-	-	91.4%	0.5%
DIM1-2	WD/WD-2							-	-	92.1%	0.2%
DIM1-2	HI	Lutron	Diva/Skylark/Skylark Contour ELV	CT-ELV-303-P	120	Reverse Phase	Wallbox	-	-	85.6%	0.3%
DIM1-2	WD/WD-2							-	-	86.4%	0.4%
DIM1-2	HI	LeGrand	450W C-L	WSCL450TCCCV4	120	Forward Phase	Wallbox	-	-	99.7%	0.6%
DIM1-2	WD/WD-2							-	-	98.9%	0.5%
DIM1-2	HI	Lutron	Homeworks QS C-L	HQRA-6CL-WH	120	Forward Phase	Wallbox/Residential System	85	24	97.4%	0.6%
DIM1-2	WD/WD-2							85	20	98.4%	0.5%
DIM1-2	HI	Lutron	Homeworks QS ND	HQRD-6ND-WH	120	Forward Phase	Wallbox/Residential System	85	16	99.0%	0.4%
DIM1-2	WD/WD-2							85	12	100.0%	0.2%
DIM1-2	HI	Lutron	Homeworks QS NA	HQRD-6NA-WH	120	Reverse Phase	Wallbox/Residential System	95	34	90.7%	0.5%
DIM1-2	WD/WD-2							95	30	91.0%	0.2%
DIM1-2	HI	Lutron	Homeworks QS	HW/LP-RPM-4U-120	120	Forward Phase	Residential System	95	11	98.7%	0.6%
DIM1-2	WD/WD-2							95	8	99.0%	0.2%
DIM1-2	HI	Lutron	Homeworks QS	HW/LP-RPM-4A-120	120	Reverse Phase	Residential System	95	16	100.0%	0.6%
DIM1-2	WD/WD-2							95	14	99.7%	0.3%
DIM1-2	HI	Lutron	Grafik Eye QS / Homeworks WPM	QSGRJ-4P-WH	120	Forward Phase	Residential/Commercial System	85	18	99.7%	0.5%
DIM1-2	WD/WD-2							85	13	99.4%	0.1%
DIM1-2	HI	Lutron	Grafik Eye 3000 / HomeWorks WPM	Grafik Eye 3506	120	Forward Phase	Residential/Commercial System	High & Low-End Trim Required		99.9%	0.5%
DIM1-2	WD/WD-2							99.2%	0.7%		
DIM1-2	HI	Vantage	UDM - INC	UDM08-EM	120	Forward Phase	Residential System	90	19	95.3%	0.3%
DIM1-2	WD/WD-2							95	17	99.9%	0.5%
DIM1-2	HI	Vantage	UDM - ELV	UDM08-EM	120	Reverse Phase	Residential System	90	18	97.5%	0.4%
DIM1-2	WD/WD-2							95	16	99.7%	0.5%
DIM1-2	HI	Vantage	SDM - INC	SDM12-EM	120	Forward Phase	Residential System	90	9	99.9%	0.6%
DIM1-2	WD/WD-2							90	6	99.9%	0.3%
DIM1-2	HI	Vantage	SDM - ELV	SDM12-EM	120	Reverse Phase	Residential System	90	8	99.9%	0.5%
DIM1-2	WD/WD-2							90	5.5	99.9%	0.4%
DIM1-2	HI	Vantage	ScenePoint Dimmer	DS15TEA-AWNA	120	Forward Phase	Wallbox/Residential System	90	8	99.8%	0.4%
DIM1-2	WD/WD-2							90	6	99.8%	0.3%
DIM3-2											
DIM3-2	HI	Lutron	Maestro Wireless ND	MRF2-6ND-120-WH	120	Forward Phase	Wallbox	-	-	99.7%	7.4%
DIM3-2	WD/WD-2							-	-	99.3%	1.9%
DIM3-2	HI	Lutron	RadioRA 2	RRD-10ND-WH	120	Forward Phase	Wallbox/Residential System	-	-	99.5%	3.0%
DIM3-2	WD/WD-2							-	-	99.1%	2.0%
DIM3-2	HI	Lutron	Diva/Skylark/Skylark Contour ELV	CT-ELV-303-P	120	Reverse Phase	Wallbox	-	-	99.3%	7.2%
DIM3-2	WD/WD-2							-	-	99.0%	5.2%
DIM3-2	HI	LeGrand	450W C-L	WSCL450TCCCV4	120	Forward Phase	Wallbox	-	-	99.4%	11.5%
DIM3-2	WD/WD-2							-	-	98.8%	8.0%
DIM3-2	HI	Lutron	Homeworks QS C-L	HQRA-6CL-WH	120	Forward Phase	Wallbox/Residential System	85	10	99.8%	3.1%
DIM3-2	WD/WD-2							85	10	99.8%	2.2%
DIM3-2	HI	Lutron	Homeworks QS ND	HQRD-6ND-WH	120	Forward Phase	Wallbox/Residential System	85	4	99.5%	4.3%
DIM3-2	WD/WD-2							85	3	99.3%	2.7%
DIM3-2	HI	Lutron	Homeworks QS NA	HQRD-6NA-WH	120	Forward Phase	Wallbox/Residential System	90	5	99.6%	5.4%
DIM3-2	WD/WD-2							90	5	99.6%	3.9%
DIM3-2	HI	Lutron	Homeworks QS	HW/LP-RPM-4U-120	120	Forward Phase	Residential System	90	7	99.5%	6.0%
DIM3-2	WD/WD-2							90	6	98.8%	3.3%
DIM3-2	HI	Lutron	Homeworks QS	HW/LP-RPM-4A-120	120	Reverse Phase	Residential System	90	2	99.5%	4.5%
DIM3-2	WD/WD-2							90	2	99.2%	3.3%
DIM3-2	HI	Lutron	Grafik Eye QS / Homeworks WPM	QSGRJ-4P-WH	120	Forward Phase	Residential/Commercial System	85	6	99.5%	3.6%
DIM3-2	WD/WD-2							85	5	98.7%	2.1%
DIM3-2	HI	Lutron	Grafik Eye 3000 / HomeWorks WPM	Grafik Eye 3506	120	Forward Phase	Residential/Commercial System	High & Low-End Trim Required		99.5%	5.3%
DIM3-2	WD/WD-2							99.8%	3.7%		
DIM3-2	HI	Vantage	UDM - INC	UDM08-EM	120	Forward Phase	Residential System	90	3	99.3%	3.2%
DIM3-2	WD/WD-2							90	3	99.9%	2.3%
DIM3-2	HI	Vantage	UDM - ELV	UDM08-EM	120	Reverse Phase	Residential System	90	2.5	99.3%	4.0%
DIM3-2	WD/WD-2							90	2.5	99.9%	2.9%
DIM3-2	HI	Vantage	SDM - INC	SDM12-EM	120	Forward Phase	Residential System	90	2.5	99.4%	3.5%
DIM3-2	WD/WD-2							90	2.5	99.8%	3.1%
DIM3-2	HI	Vantage	SDM - ELV	SDM12-EM	120	Reverse Phase	Residential System	90	2.5	99.5%	3.8%
DIM3-2	WD/WD-2							90	2.5	99.8%	3.4%
DIM3-2	HI	Vantage	ScenePoint Dimmer	DS15TEA-AWNA	120	Forward Phase	Wallbox/Residential System	90	3.5	99.4%	5.9%
DIM3-2	WD/WD-2							90	3.5	99.8%	4.3%

Dimmer compatibility testing performed by Number Eight Lighting Company using 120V/60Hz supply.
 Variations in supply power may require adjustments to recommended trim settings and/or affect dimming performance.
 The design, specification, or performance of compatible dimmers is subject to change without notice.
 For questions regarding the compatibility of dimmer models not listed above, please contact Number Eight Lighting customer service at (707) 794-0888.